

3GVR-AR - 1218-85/204 MHz
6-outputs, 2 Data, 4 TV ports


HOME AMPLIFIERS

3GVR-AR

The 3GVR-AR platform is a 1.2 GHz DOCSIS® 3.1 amplifier with 6 Ports. The products come equipped with 2 bidirectional DATA ports and 4 unidirectional TV ports. The 3GVR-AR085 has an 85 MHz, and the 3GVR-AR204 a 204 MHz upstream path. The amplifier comes with a highly efficient power supply designed for eco-friendly operation, saving energy without compromising performance, capacity, or stability.

3GVR-AR platform features

- Frequency range up to 1218 MHz, DOCSIS® 3.1 compliant
- 6 user ports compact amplifier
- Outer plastic cover to secure against electrical contacts
- Forward path with differentiated gain according to ports
- Energy saving power supply
- Data ports equipped with 75 Ohm terminators
- Fixed power cord



HOME AMPLIFIER / 3GVR-AR

TECHNICAL SPECIFICATIONS ⁽¹⁾			
Downstream signal path		Upstream signal path	
Frequency range	105/258...1218 MHz	Frequency range	15...85/204 MHz
Gain		Gain	
DATA1	2 dB	DATA1	1 dB
DATA2	2 dB	DATA2	1 dB
TV0	0 dB		
TV1	4 dB		
Return loss	18 dB	Return loss	18 dB
Noise figure	≤ 6.5 dB	Noise figure	≤ 15 dB
Isolation	25...30 dB	Ingress suppression	30 dB
U_{max}	84-88 dBμV		
GENERAL SPECIFICATIONS ⁽¹⁾			
Connectors	F female, moulded	Dimensions	22 × 9.5 × 4 cm (w × h × d)
Supply voltage	220...240 VAC	Operating temperature	-5...+40 °C
Power consumption	4 W	ESD	4 kV
Surge	1 kV		
NOTES			
(1) Typical values, please contact a Teleste representative for further information.			
ORDERING INFORMATION			
3GVR-AR085	Home amplifier, 15...1218 MHz, with 85 MHz upstream path. F termination on both DATA ports and customer specific logo.		
3GVR-AR204	Same as above, but with 204 MHz upstream path.		
INSIGHTS			
 NO NEED FOR ALIGNMENT...		 LOGISTICS...	
<p>Everyone demands ease of installation. That's why our Home Amplifiers require no alignment or adjustments — just power them on.</p>		<p>Home Amplifiers are delivered in high volumes, and fast deliveries are essential. Teleste's logistics services are tailored and aligned with each customer's requirements.</p>	

TELESTE

TELESTE CORPORATION

www.teleste.com

Home Amplifier 3GVR-AR_260209

Copyright © 2026 Teleste Corporation. All rights reserved. Teleste and the Teleste logo are registered trademarks of Teleste Corporation. Other product and service marks are property of their respective owners.

Teleste reserves the right to make changes to any features and specifications of the products without prior notice. Although the information in this document has been reproduced in good faith, the contents of this document are provided "as is". Teleste makes no warranties of any kind in relation to the accuracy, reliability or contents of this document, except as required by applicable law.